

# Wall Mounted Power Supplies

## 12VDC/24VAC



### Features

- LED voltage display
- Battery backup
- Mains fail and low battery contacts
- Lockable front door
- Internal GPO recess
- Short circuit & overload protection
- Cooling by free air convection
- Individually fused outputs
- LED indicators on all outputs
- Battery back (options)
- Tamper switch (option)
- User adjustable voltage for DC units
- Low battery signal (11 or 22V DC) for DC units
- Low voltage cut off (10 or 20V DC) for DC units



### Specifications

Model	Description	Dimensions (WxDxH)
<b>24V AC</b>		
W-AC24-4A	24V AC, 4A, 9 x 1A Outputs	362x92x235mm
W-AC24-8A	24V AC, 8A, 16 x 1A Outputs	362x92x235mm
W-AC24-16A	24V AC, 16A, 32 x 1A Outputs	345x120x435mm
W-AC24-25A	24V AC, 25A, 32 x 1A Outputs	345x120x435mm
<b>12V DC</b>		
W-DC12-4A	12V DC, 4A, 9 x 1A Outputs	362x92x235mm
W-DC12-8A	12V DC, 8A, 16 x 1A Outputs	362x92x235mm
W-DC12-12A	12V DC, 12A, 16 x 1A Outputs	362x92x235mm
W-DC12-12C4	13.5V DC, 8A, 16 x 1A Outputs	362x92x235mm
W-DC12-24A	12V DC, 25A, 32 x 1A Outputs	345x120x435mm
<b>13.5V DC</b>		
WB-DC12-4A	13.5V DC, 4A, 9 x 1A Outputs, with 1 x 9AH/12V Battery	362x92x235mm
WB-DC12-8A	13.5V DC, 8A, 16 x 1A Outputs, with 1 x 9AH/12V Battery	362x92x235mm
WB-DC12-12A	13.5V DC, 12A, 16 x 1A Outputs, with 1 x 9AH/12V Battery	362x92x235mm
WB-DC12-24A	13.5V DC, 24A, 32 x 1A Outputs, with 1 x 9AH/12V Battery	345x120x435mm

Specifications subject to change without prior notice.