

Control and signalling Units – Contact blocks



SUMMARY	PAGES
1. Description, use	1
2. Range	1
3. Measurement	2
4. Installation	6
5. Technical characteristics	8
6. Compliance and approvals	9
7. Equipment and Accessories	10

1. DESCRIPTION - USE

Contact Block and illuminated block to be used with control unit

2. RANGE References

33E01 33E10 33E11 33E10Y7 33E01Y7 33EAWL 33EARL
33EAGL 33EABL 33EAYL 33EAWL4 33EARL4 33EAGL4 33EABL4
33EAYL4 33EAWM 33EARM 33EAGM 33EABM 33EAYM
33EAWH 33EARH 33EAGH 33EABH 33EAYH 33ET 33ETT
33EFM 33EFH 33EHC 33ELC LM11 331E10 331E01 333E01
333E10 333E02 333E20 333E11 333E21 333E12 333E03
334EAWL22 334EARL22 334EAGL22 334EABL22 334EAYL22
334EAWM22 334EARM22 334EAGM22 334EABM22
334EAYH22 334EAWH22 334EARH22 334EAGH22 334EABH22
334EAYH22 333EAWL10 333EARL10 333EAGL10 333EAWL11
333EARL11 333EAGL11 333EAWL20 333EARL20 333EAGL20
333EAWH10 333EARH10 333EAGH10 333EAWH11 333EARH11
333EAGH11 333EAWH20 333EARH20 333EAGH20 33D01
33D10 331ED01 331ED10 33R01 33R10 33EAWL 33RARL
33RAGL 33RABL 33RAYL 33EAWM 33RARM 33RAGM 33RABM
33RAYM 33EAWH 33RARH 33RAGH 33RABH 33RAYH 33RFM
33RFH 331ER01 331ER10 333ER20 333ER01 333ER11 333ER02
331ERAWL 331ERARL 331ERAGL 331ERABL 331ERAYL
331ERAWM 331ERARM 331ERAGM 331ERABM 331ERAYM
331ERAWH 331ERARH 331ERAGH 331ERABH 331ERAYH
333EP02 333EP20 33PAWL 33PARL 33PAWL 33PAYL 33P01
33P10 33P01Y7 33P10Y7 33S01 33S10 33SAWL 33SARL
33SAGL 33SABL 33SAYL 33SAWM 33SARM 33SAGM 33SABM
33SAYM 33SAWH 33SARH 33SAGH 33SABH 33SAYH 33E01C
33EAWMD

Type of use:

Contact Block, LED Module, Joystick Block, Lamp-test Block,
Transformer Block, Filter Block

Connection: Screw terminals, Plug-In terminals, Faston terminals,
Pin style terminals

2. RANGE

. Mounting

- . Front mounting with a clip
- . Base mounting (control station)

. Electrical Rating

(Standard IEC 60947-5-1 – max rating , see page 6)

. For screw terminals and plug-in terminals :

- . Alternating current (AC-15): 120 V ≤ Ue ≤ 600 V
6 A ≥ Ie ≥ 1,2 A
- . Direct current (DC-13): 125 V ≤ Ue ≤ 600 V
0,55 A ≥ Ie ≥ 0,1 A

. For Pin style connection :

- . Alternating current (AC-15): 120 V ≤ Ue ≤ 240 V
3 A ≥ Ie ≥ 1,5 A
- . Direct current (DC-13): 125 V ≤ Ue ≤ 250 V
0,22 A ≥ Ie ≥ 0,1 A

. For Faston terminals :

- . Alternating current (AC-15): 120 V ≤ Ue ≤ 240 V
6 A ≥ Ie ≥ 3 A
- . Direct current (DC-13): 125 V ≤ Ue ≤ 250 V
0,55 A ≥ Ie ≥ 0,27 A

. For LED Blocks:



- . 12 to 24 V AC/DC ±10%
- . 48 V AC/DC ±10%
- . 110 V DC – 8% / +15%
- . 130 V AC – 8% / +15%
- . 230 V AC ±15%

. Minimum operating current :

- . Standard blocks (screws, plug-in, faston, pin style terminals)
. Ue= 24 V DC and Ie= 5mA
- . Low level contact blocks (screws, pin style)
. Ue= 5 V DC and Ie= 1 mA



3. MEASUREMENT

Screw terminal block , single clip





Screw terminal block , 3 position clip

64.5 with 2nd row contact
block or double block





3. MEASUREMENT

Screw terminal block, 5 position clip




Plug-in terminal block, single clip




3. MEASUREMENT

Plug-in terminal block, 3 position clip




Plug-in terminal block, 5 position clip




3. MEASUREMENT

Faston terminal block, single clip




Faston terminal block, 3 position clip




3. MEASUREMENT

Pin-style terminal block, single clip




Pin-style terminal block, 3 position clip




3. MEASUREMENT


Drill plan for Pin-style terminal blocks on Printed Circuit Board (PCB)



Screw terminal contact block




Plug-in terminal contact block




3. MEASUREMENT


Faston terminals contact block



Pin-style terminal contact block




Pin-style terminal contact




3. MEASUREMENT


Plug-in terminals LED block



Plug-in terminals LED block




Pin-style terminals LED block




3. MEASUREMENT

Joystick block (screw terminal)



Double block (screw terminal)




4. INSTALLATION


Front panel mounting :

- . With single clip
- . Clip and head assembly


Clip marker on the top




- . block assembly / removal on/of clip




4. INSTALLATION




- . with 3 and 5 position clip
- . Clip and head assembly



- . contact block assembly / removal on/of clip



4. INSTALLATION



Control station mounting :

- . use base mounting contact blocks

Printed circuit board mounting :

- . use Pin-style contact blocks

Current supply :

- . On the back side of the block

Visualization of the contact state:

- . Contact state is visible at the back side of the contact block, mounted block (colour plunger, visible)

Type of wire :

For screw terminal contact blocks (front mounting or base mounting):

- . Solid or stranded wire without ferrule : 2x 0,5 mm² to 2x 2,5 mm²
- . Solid or stranded wire with ferrule : 2 x 0,5 mm² to 2 x 1,5 mm²

For plug-in terminal contact blocks:

- . Solid or stranded wire without ferrule : 2x 0,5 mm² to 2x 2,5 mm²
- . Solid or stranded wire with ferrule : 2 x 0,5 mm² to 2 x 1,5 mm²

For Faston terminal contact blocks :

- . 1 faston clip 6,35 mm or 2 faston clips 2,85 mm

For pin style terminal contact blocks :

- . Ø 1 mm

Connection with screw and plug-in terminals :

- . Terminals protected against direct contact (IP2X)
- . Recommended terminal torque: 1.2 Nm

Creation date: 08/04/2018

4. INSTALLATION

Tools :

- . For plug-in terminals, it is advisable to use screwdriver with Flat blade - 2.5 mm
- . For screw terminals, it is advisable to use screwdriver Phillips n°2 or screwdriver with flat blade - 5,5 mm
- . To remove the block it is advisable to use a flat blade screwdriver


Connecting blocks on clips :

		Clip		
		single	3 positions	5 positions
Blocks	1 level	X	X	X
	2 levels		X	


6 and more NO blocks on a 3 position clip are unsuitable with ISO13850 push and turn mushroom head.

Push to test LED pilot light diagram:


Lamp testing module with 1 diode for direct supply 24V and 48V AC/DC



Lamp testing module with 2 diodes for direct supply 24V and 48V AC/DC



Lamp testing assembly for direct supply 130V and 230V AC



Filter Block:

Filter block to be wired in parallel to the LED block

Update : 03/07/2018

BACO

5. TECHNICAL CHARACTERISTICS

Maximum operating current:

- . For standard blocks (screw or Plug-in terminals)

- . AC15 (Alternating current)

- Ue = 120 V Ie = 8 A
- Ue = 230 V Ie = 6 A
- Ue = 400 V Ie = 4,5 A
- Ue = 440 V Ie = 3,5 A
- Ue = 500 V Ie = 2,5 A
- Ue = 690 V Ie = 1 A

- . DC13 (Direct current)

- Ue = 24 V Ie = 1,5 A
- Ue = 48 V Ie = 1 A
- Ue = 60 V Ie = 0,7 A
- Ue = 110 V Ie = 0,3 A
- Ue = 230 V Ie = 0,2 A

- . For Pin style terminal blocks

- . AC15 (Alternating current)

- Ue = 120 V Ie = 8 A
- Ue = 240 V Ie = 6 A
- Ue = 400 V Ie = 4 A

- . DC13 (Direct current)

- Ue = 125 V Ie = 0,22 A
- Ue = 250 V Ie = 0,1 A

- . For Faston terminal blocks

- . AC15 (Alternating current)

- Ue = 120 V Ie = 6 A
- Ue = 240 V Ie = 3 A

- . DC13 (Direct current)

- Ue = 125 V Ie = 0,55 A
- Ue = 250 V Ie = 0,27 A

- . For joystick blocks

- . AC15 (Alternating current)

- Ue = 60 V Ie = 10 A
- Ue = 110 V Ie = 6 A
- Ue = 220 V Ie = 3 A
- Ue = 380 V Ie = 2 A
- Ue = 500 V Ie = 1,5 A
- Ue = 600 V Ie = 1,2 A

- . DC13 (Direct current)

- Ue = 24 V Ie = 2,5 A
- Ue = 48 V Ie = 1,4 A
- Ue = 60 V Ie = 1 A
- Ue = 110 V Ie = 0,55 A
- Ue = 220 V Ie = 0,27 A
- Ue = 300 V Ie = 0,2 A

Conventional thermal current in enclosure :

- . For standard blocks (screw or Plug-in terminals)

- . Ith = 16 A in AC
- . Ith = 2,5 A in DC

- . For Faston terminal blocks

- . Ith = 10 A in AC
- . Ith = 2,5 A in DC

- . For Pin style terminal blocks

- . Ith = 5 A in AC
- . Ith = 1 A in DC

Rated insulation voltage :

- . For screw terminal contact blocks
 - . Ui = 690 V according to IEC 60947-5-1
 - . Ui = 600 V according to UL508
- . For Faston terminal blocks
 - . Ui = 320 V according to IEC 60947-5-1
 - . Ui = 300 V according to UL 508
- . For LED blocks
 - . Ui = 300 V according to IEC 60947-5-1
- . For Pin-style terminal blocks
 - . Ui = 250 V according to IEC 60947-5-1

Pollution degree :

- . 3

Rated impulse withstanding voltage :

- . For standard contact and faston blocks
 - . Uimp = 6kV according to IEC 60947-5-1
- . For LED and Pin-style terminal blocks
 - . Uimp = 4kV according to IEC 60947-5-1

LED blocks :

- . Life time:
 - red and yellow 100 000 hours at 25°C under Un
 - other colours 50 000 hours at 25°C under Un
- . LED power consumption:
 - . For 24 V = 25 mA
 - . For 48 V = 15 mA
 - . For 110 VDC = 20 mA
 - . For 130 V = 20 mA
 - . For 230 V = 16 mA
- . Operating voltage : 12, 24, 48V AC/DC, 110V DC, 130, 230 V AC
- . Frequency: 50 or 60 Hz
- . Electromagnetic compatibility :
 - . Electrostatic discharge immunity test according test IEC 61000-4-2 level 2
 - . Radiated, radio-frequency, electromagnetic field immunity test according to IEC 61000-4-3 level 3
 - . Electrical fast transient/burst immunity test according to IEC 61000-4-4 :
 - . Level 2 for Un = 24 to 48 V
 - . Level 3 for Un = 110 to 230 V
 - . Surge immunity test 1,2 / 50 µs according to IEC 61000-4-5 :
 - . Level 2 for Un = 24 to 48 V
 - . Level 3 for Un = 110 to 230 V
 - . Immunity to conducted disturbances, induced by radio-frequency fields according to IEC 61000-4-6
 - . Voltage dips, short interruptions and voltage variation immunity tests according to IEC 61000-4-11 only on models Un = 100 to 230V

Protection Fuse :

- . For the standard blocks
 - . 10 A gG according to IEC 60947-5-1
- . For pin-style terminal blocks
 - . 6 A gG according to IEC 60947-5-1

Mechanical life :

- . For screw, Faston and pin-style terminal blocks
 - . 5 000 000 cycles

5. TECHNICAL CHARACTERISTICS

Electrical operating life :

- . For screw, faston and pin-style terminal blocks
- . 1 000 000 cycles:
 - AC15 – B300
 - . Ue = 120 V Ie = 3 A
 - . Ue = 240 V Ie = 1,5 A
 - DC13 – R300
 - . Ue = 125 V Ie = 0,22 A
 - . Ue = 250 V Ie = 0,1 A

Operating Temperature :

- . minimum : -25°C maximum : +70°C

Storage temperature :

- . minimum : -40°C maximum : +70°C

Cold test :

- . according to IEC 60068-2-1

Dry heat test :

- . according to IEC 60068-2-2

Constant humidity test :

- . according to IEC 60068-2-3 / IEC 60068-2-30

Glow wire test :

- . 960°C on the blocks

Marking :

- . Front part marking NC Screw terminal block



Rear marking NC Block



5. TECHNICAL CHARACTERISTICS

Quantity-packaged :

- .by 1, 5, 10 or 20

Protection degree against direct contacts:

- . IP2X according to IEC 60529 (screw and plug-in terminals)

6. COMPLIANCE AND APPROVALS

Standard compliances:

- . IEC 60947-5-1
- . IEC 60947-5-5
- . IEC 60947-5-4
- . UL 508
- . CSA 22.2
- . CCC

Approvals:

- . cULus and Bureau Véritas (Marine rules)
- . BBJ

Environmental respect.

- . Compliant to the directive 2002/95/CE of 27/01/03 « RoHS » restricts the use of hazardous substances like lead, mercury, cadmium, hexavalent chromium, poly brominated diphenils (PBBs) and poly brominated diphenils ethers (PBDEs) since July 1st 2006
- . Compliant to the directives 91/338/CEE of 18/06/91 and decree 94-947 of 27/07/04
- . Compliant to the directive 72/23 CEE and 89/339 CEE on the CE marking
- . Compliant to the directive 73/374 CEE (98389 rule of the 15/05/98)
- . Compliant to the directive 76/769/CEE concerning hazardous substances prohibition

Plastic materials :

- . Plastic material body halogen free
- . base and cover : polyamid
- . plunger : polyamid

Metallic materials :

- . Terminals : Steel
- . Contact : Silver
- . Golden contact : gold flash 2,5 µm

Packaging:

- . Packaging development and manufacturing conform to the decree 98-638 of 20/07/98 and to the directive 94/62/CE

7. EQUIPEMENT AND ACCESSORIES

. Specials blocks :

- For joystick (screw terminals)
- Lamp test (screw terminals)
- Transformer block (screw terminals)
- Filter block (screw terminals or plug-in terminals)
- Junction block (screw terminals)
- Empty block

. Accessories

- single clip
- 3 position clip
- 5 position clip