


# Dialguard™ Relay Interface



To complete our Dialguard™ voice diallers we have introduced a range of interface modules that expand the functionality of both the DT1 and the DT6I. The DRI24 allows for 24 VDC power sources to be used with either dialler and provides 2 relay outputs for the DT6I. The DRI simply provides a 2 relay output for the DT6I.

**NIDAC**

*dialguard*

# FEATURES

## DRI Features

- Relay Contacts  
30 Volts A.C/D.C., 5Amps, SPDT
- Connections  
6 screw terminals & 10 pin IDC socket
- Dimensions  
104mm x 72mm x 27mm, wire lead length 300mm
- Weight  
115 grams

## DRI24 Features

- Relay Contacts  
30 Volts A.C/D.C., 5Amps, SPDT
- Connections  
14 screw terminals & 10 pin IDC socket
- Dimensions  
104mm x 72mm x 27mm, wire lead length 300mm
- Weight  
135 grams
- Input Voltage  
15 to 30 Volts D.C
- Input Current  
300mA maximum
- Output Voltage  
12 Volts D.C.  $\pm$  5%
- Output Current  
250mA maximum
- Control Inputs  
+8 to 30 Volts D.C for active high  
0 to + 2 Volts D.C for active low

**dialguard** 

Distributed By:

Manufactured by:  
Nidac Security P/L

2 Cromwell Street, Burwood, Vic 3125 Australia  
ph + 61 3 9808 6244 fx + 61 3 9808 9335  
www.nidac.com email: sales@nidac.com

