

# Elevation Network Adaptor



Lockwood Elevation™ Network Adaptor has been designed so you can connect Elevation to any 3rd party wall switch\* or home automation system. This flexibility allows connection to virtually any system or switch.

## Switch Types

N/O: (Normally open) bell press switches are required; e.g. momentary/non latching.

We recommend the below parts that can be acquired at any electrical wholesaler:

HPM Part # 770XM  
PDL Part# 681M20P  
Clipsal Part# 30MBPR

## Functions

### Wall Switch

For standard wall switch operation; the network adaptor connects to the wall switch, and allows up to 30 windows to be controlled by that wall switch. The network adaptor will typically sit behind the switch. This is normally used for instances where users want to control 1-30 windows per room.

## Cbus or Home Automation

The Elevation Network Adaptor can also be connected to a home automation or fire control system. The network adaptor is hardwired to the "panel" and 1 output can control up to 30 windows. This is normally used for instances where users want complete control of all devices in a home from one single keypad or controller.

The system's relays will be programmed to fully open and close the window other pre-sets can also be programmed.

\* Momentary bell press type

## Product Details

<b>Dimensions</b>	58H x 43W x 17D
<b>Materials</b>	Durable PVC Black
<b>Voltage</b>	12-24vdc
<b>Current</b>	50ma
<b>Environment</b>	Operational Temperature 0° to +60°
<b>Humidity</b>	90% @ 35°C
<b>Input</b>	2 x Potential Free (1 x Open 1 x Close)
<b>Output</b>	CAN bus Data (white + brown)



Cbus Home Automation



Wall Switch