

SECOR® Resettable Emergency Door Release with LED and buzzer built in

DWS201



Specifications

- Power: 12/24VDC
- Operating current:
 - 12VDC - 18mA standby; 75mA operation
 - 24VDC – 11mA standby; 41mA operation
- Buzzer: can be turned off or on; continuous tone and pulse sound selectable; volume adjustable
- LED:
 - Green standby; red in emergency
 - Red emergency LED: can be turn off or on; flashing or steady selectable
- Contacts: Isolated 3 x NO and NC
- Contacts max load: 125V/3A
- Colour: White, green
- Plastic reset key included
- Protection covers available
- Dimensions: 90 x 93 x 64mm